

Installation Instructions

INSTRUCTIONS PERTAINING TO A RISK OF FIRE, OR INJURY TO PERSONS. IMPORTANT SAFETY INSTRUCTIONS

Warning! To reduce the risk of FIRE OR INJURY TO PERSONS:

1. Do not touch luminaire while lamp is on. Turn off/unplug and allow to cool before replacing lamp.
2. Lamp gets HOT quickly! Contact only switch/plug when turning on.
3. Do not touch hot luminaire or mount option.
4. Keep lamp away from materials that may burn.
5. Do not touch lamp at any time. Use a soft cloth. Oil from your skin may damage lamp.
6. Do not operate the luminaire or mount option with damaged or missing parts.
7. Do not disassemble mount option.
8. Do not install luminaire within 10 feet of a pool, spa, or fountain.
9. Have luminaire and mount option installed in accordance with all applicable installation codes and standards by a person familiar with the construction and operation of the fixture and the hazards involved.
10. For use with low voltage lighting fixtures and remote transformers only.
11. Use only cable rated for low voltage. Cable buried more than 6" must be suitable for direct burial. Direct burial cable may be ordered from Vision3 Lighting.

SAVE THESE INSTRUCTIONS

Installation

1- Mounting Luminaire

- 1a - Feed the two leads of the **Luminaire** thru the mount hole in the **Canopy**.
- 1b - Insert the **Luminaire** knuckle into the **Canopy** mount hole.
- 1c - Feed the two leads of the **Luminaire** thru the **Lock Nut**.
- 1d - Tighten the **Lock Nut** to attach the **Luminaire** to the **Canopy**.

2- Electrical Connections

- 2a - Feed the **Low Voltage Supply Cable** through the **Wiring Hole** on the bottom of the **Canopy**.
- 2b - Attach the **Low Voltage Supply Cable** to the **Luminaire** leads by using watertight connectors. Note: Check that the **Luminaire** and supply cable are rated for the supply power.
- 2c - Tuck all wiring and connectors into the **Canopy**.

3- Final Mounting

- 3a - Position the **Canopy** on the **Tree** so the **Luminaire** is aimed in the desired direction.
- 3b - Mount the **Canopy** to the **Tree** using **Nails or Screws** sized appropriately for holding the weight of the **Luminaire** and **Canopy** to the **Tree**.
- 3c - Secure the **Low Voltage Supply Cable** to the **Tree**.
- 3d - Inspect all wiring connections.
- 3e - Connect to low voltage source power.

