



www.FireFarm.com

Assembly Instructions

Twist Pendant Pod Pendant

Twist 1F-P-8
Pod 1G-P-8



Parts Included:

- 1- Cord set with socket assembly and ceiling canopy
- 1-Glass shade
- 1-spacing tube
- 1-white plastic pheno ring for POD or 2 white plastic pheno rings for TWIST
- 1-Bulb



Twist socket parts



Pod socket parts

Assembly:

1. Mount cord set and ceiling canopy per separate installation instructions included with ceiling canopy.
2. **(Figure 1)** Insert socket through hole in top of shade. Slide shade up cord beyond the socket and grasp the cord above the socket. The shade may rest on the back of your hand or grasp it per figure 2.
3. **Twist only: (Figure 2)** Screw plastic pheno ring onto the socket with the large side toward the shade. Screw the ring completely past the socket so it is free on the cord above the socket.
4. **Twist and Pod: (Figures 3 & 4)** Slide the spacing tube over the socket and hold it above the socket.
5. **(Figure 4)** Screw the plastic pheno ring onto the socket with the smaller side toward the shade. The bottom of the socket should be about even with the bottom of the phenol ring.
6. **(Figure 5)** Lower the spacer tube assembly to rest on the lower phenol ring.
7. **(Figure 6)** Lower the shade to rest on the spacer tube assembly and center the cord in the hole.
8. **Twist only:** Raise or lower the bottom plastic pheno ring so the hole in the glass shade at the top is flush with the centering washer on the cord.
9. Insert the enclosed bulb, turn on the power and enjoy your pendant



Figure 1



Figure 2



Figure 3




Figure 4



Figure 5



Figure 6

BULB: Candelabra base type G 120v 60W bath and vanity

IMPORTANT SAFETY INFORMATION

If your lamp has a plug:

This portable lamp has a polarized plug (one blade is wider than the other) as a feature to reduce electric shock. This plug will fit in a polarized outlet only one way. If the plug does not fit fully in the outlet, reverse the plug. If it still does not fit, contact a qualified electrician. Never use with an extension cord unless plug can be fully inserted. Do not alter the plug.

If your lamp does not have a plug:

WARNING: RISK OF FIRE AND ELECTRIC SHOCK. THIS PRODUCT IS TO BE INSTALLED ONLY BY A QUALIFIED ELECTRICIAN.