

General Installation Instructions

READ AND FOLLOW ALL SAFETY INSTRUCTIONS!
SAVE THESE INSTRUCTIONS AND DELIVER TO OWNER AFTER INSTALLATION

⚠ WARNING

To reduce the risk of death, injury or property damage from fire, electric shock, cuts, abrasions, falling parts, and other hazards:

- Service of the equipment must be performed by qualified service personnel.
- Installation and maintenance must be performed by a person familiar with the construction and operation of this product and any hazards involved. All applicable codes and ordinances must be followed.
- Read this document before installing, servicing, or maintaining this equipment or installing a lamp. These instructions do not cover all installation, service, and maintenance situations. If your situation is not covered, or if you do not understand these instructions or additional information is required, contact Peerless Lighting or your local Peerless Lighting Distributor.
- Read and follow all warnings and instructions provided by the lamp manufacturer.

⚠ WARNING

Before installing, servicing, or maintaining this equipment, follow these general precautions. To reduce the risk of electrocution:

- Make sure the equipment is properly grounded.
- Always de-energize the circuit and/or equipment before connecting to, disconnecting from, or servicing the equipment.

To prevent fixture row from over-current:

- By adding the input current of each fixture section marked on the fixture, the total current per power feed must not exceed the maximum line wire amperage marked on the fixture and the power feed cord/wire amperage rating whichever the least.

To reduce the risk of fire:

- Keep material away that can burn from hot lamp.
- Make sure lamps are correctly installed.
- Use supply conductors with a minimum installation temperature rating as specified on equipment.

To reduce the risk of personal injury from cuts, abrasions, or falling parts:

- Wear gloves to prevent cuts or abrasions from sharp edges when removing from carton, handling and maintaining this equipment.
- Do not use abrasive materials, glass cleaners or other solvents on reflector or lens. These substances may damage equipment and cause parts to eventually break and fall.
- Do not install a damaged fixture.

⚠ CAUTION

Observe lamp manufacturer's recommendations and restrictions on lamp operation, including but not limited to ballast type, burning position, replacement and cycling. Use only lamps that comply with applicable ANSI standards.

NOTICE: If lamp is marked (Hg) it contains mercury. Follow disposal laws. See www.lamprecycle.org

Peerless Lighting, a division of Acuity Brands Lighting, Inc., assumes no responsibility for claims arising out of improper or careless installation or handling of this product.

SAVE THESE INSTALLATION INSTRUCTIONS

Part Number: PIN004100 Revision: C Effective Date: 12/20/2010 ECO3618

NARO™ T8 Pendant Mount

Installation Instructions

PIN004002 Rev. 01 03/12 ECO3640

NRM9


These installation instructions are used for installing the following fixtures and kits:

Fixture	End-cap Kit	Option
NRM9	NRMT8EP	DU

WARNING: Please read the "important safety instructions" prior to installation of this product.


- A) Cable Mounting Fixture Run Installation..... page 1-2
 B) DU (Dust Cover) Installation..... page 2

SUPPORT SPACING FOR 4', 8' & 12'




KEY
 ● Support or Feed location

Using internal joiners, 4', 8' and 12' sections can be joined to form longer rows.




Adjustable Cable


1. Attach adjustable cable gripper (ACG)




IMPORTANT




Do NOT insert cable into ACG prior to ACG being attached to fixture. Twisting the cable could cause gripper to become loose.




1. Locate first fixture. Screw support cable stud onto fixture joiner. Insert power cord & bushing through knockout on the first fixture at the male connector end. Connect wire harnesses and gently insert wires back inside fixture.



2. Secure cable studs into joiner on other end of the fixture. Adjust the cable studs to level the fixture.




3. Raise the next fixture into position and connect wire connectors. Securely join fixtures with two 1/4-20 screws. Adjust the cable studs to level the fixtures. Repeat Step 2 & 3 until last fixture in the row is installed.



4. Install end-cap by securing two provided #10 screws with split washer in between.

B) DU (Dust Cover) Installation



For Optional DU (Dust Cover) on all NRM fixtures, simply remove the DU to re-lamp during maintenance and then restore the part by overlaying typically as shown on the left to cover the lamp.

Used On	Mounting Kit Name (Accessories)	
	Fixed Cable	Adjustable cable
Support location at normal power feed	NRMT8FK	ACGPFK
Support location at emergency power feed	NRMT8EK	ACGPEK
Support location without power feed	NRMT8SK	ACGPSK