



TRANSFORMER SERIES

Standard Features on 12 Volt and 24 Volt Transformers



- Compact size
- Outdoor rated NEMA 3R (Indoor or outdoor rated)
- Available in black powder coat or stainless steel
- 10% boost tap available (Compensation for longer runs)
- Whisper quiet operations
- Dimmable
- Standard re-settable primary breaker
- Easy installation and accessible maintenance
- Highest degree of efficiency
- Available in alternating current (AC) for standard lamps or direct current (DC) for LEDs
- UL and cUL approved
- Consult factory for other input voltages

Class II 12 Volt Transformer (Indoor Rated) - Primary and Secondary Fusing Included



Product Codes

Lamps: TRA300-6F/120V/12VAC or TRA300-6F/277V/12VAC

LEDs: TRA300-6F/120V/12VDC or TRA300-6F/277V/12VDC

Features:

- 300VA maximum load
- Six inch lead wire
- 97.9% power factor
- 120 volts or 277 volts at 60 Hertz
- Six 5 - amp circuits in secondary
- Dimensions: 7" W x 7" H x 3 3/16" D
- 12.8 open circuit volts
- 11.5 output volts
- 0.3 open circuit current (amps) and 2.6 input current (amps)

Class I Transformer (Indoor or Outdoor Rated NEMA 3R) - Primary Fusing Included

Product Code	Max Watts	Input	Output	Input Current No Load/Full Load	Open Circuit	Power Factor	Width (W)	Height (H)	Depth (D)	
TRA 150	TRA150/120V/12VAC OR 24VAC	150	120V	12V OR 24V	0.4 / 1.4 Amps	13 or 26 Volts	0.961	3 7/16"	7 1/2"	2 15/16"
	TRA150/277V/12VAC OR 24VAC	150	277V	12V OR 24V	0.2 / 0.6 Amps	13 or 26 Volts	0.961	3 7/16"	7 1/2"	2 15/16"
	TRA150/120V/12VDC OR 24VDC	150	120V	12V OR 24V	0.4 / 1.4 Amps	13.5V or 26 Volts	0.961	4 3/32"	8"	3 3/32"
	TRA150/277V/12VDC OR 24VDC	150	277V	12V OR 24V	0.2 / 0.6 Amps	13.5V or 26 Volts	0.961	4 3/32"	8"	3 3/32"
TRA 250	TRA250/120V/12VAC OR 24VAC	250	120V	12V OR 24V	0.3 / 2.2 Amps	12.8V or 25.6 Volts	0.964	4 3/32"	8"	3 3/32"
	TRA250/277V/12VAC OR 24VAC	250	277V	12V OR 24V	0.12 / 1.0 Amps	12.8V or 26.6 Volts	0.964	4 3/32"	8"	3 3/32"
	TRA250/120V/12VDC OR 24VDC	250	120V	12V OR 24V	0.3 / 2.2 Amps	12.8V or 26.6 Volts	0.964	4 3/32"	8"	3 3/32"
	TRA250/277V/12VDC OR 24VDC	250	277V	12V OR 24V	0.12 / 0.8 Amps	12.8V or 26.6 Volts	0.964	4 3/32"	8"	3 3/32"
TRA 300	TRA300/120V/12VAC OR 24VAC	300	120V	12V OR 24V	0.3 / 2.6 Amps	12.8V or 25.6 Volts	0.979	4 3/32"	8"	3 3/32"
	TRA300/277V/12VAC OR 24VAC	300	277V	12V OR 24V	0.12 / 0.8 Amps	12.8V or 26.6 Volts	0.979	4 3/32"	8"	3 3/32"
	TRA300/120V/12VDC OR 24VDC	300	120V	12V OR 24V	0.3 / 2.6 Amps	12.8V or 26.6 Volts	0.979	4 3/32"	8"	3 3/32"
	TRA300/277V/12VDC OR 24VDC	300	277V	12V OR 24V	0.12 / 1.2 Amps	12.8V or 26.6 Volts	0.979	4 3/32"	8"	3 3/32"
TRA 500	TRA500/120V/12VAC OR 24VAC	500	120V	12V OR 24 V	0.4 / 4.3 Amps	2 x 12.8V or 1 x 25.6V	0.973	4 19/32"	9 13/32"	4 3/32"
	TRA500/277V/12VAC OR 24VAC	500	277V	12V OR 24V	0.15 / 1.8 Amps	2 x 12.8V or 1 x 25.6V	0.973	4 19/32"	9 13/32"	4 3/32"
	TRA500/120V/12VDC OR 24VDC	500	120V	12V OR 24V	0.4 / 4.3 Amps	2 x 12.8V or 1 x 25.6V	0.973	6 25/32"	10 19/64"	5 5/8"
	TRA500/277V/12VDC OR 24VDC	500	277V	12V OR 24V	0.15 / 1.8 Amps	2 x 12.8V or 1 x 25.6V	0.973	6 25/32"	10 19/64"	5 5/8"
TRA 600	TRA600/120V/12VAC OR 24VAC	600	120V	12V OR 24V	0.8 / 5.3 Amps	2 x 12.8V or 1 x 25.6V	0.978	4 19/32"	9 13/32"	4 3/32"
	TRA600/277V/12VAC OR 24VAC	600	277V	12V OR 24 V	0.3 / 2.3 Amps	2 x 12.8V or 1 x 25.6V	0.978	4 19/32"	9 13/32"	4 3/32"
	TRA600/120V/12VDC OR 24VDC	600	120V	12V OR 24V	0.8 / 5.3 Amps	2 x 12.8V or 1 x 25.6V	0.978	6 25/32"	10 19/64"	5 5/8"
	TRA600/277V/12VDC OR 24VDC	600	277V	12V OR 24V	0.3 / 2.3 Amps	2 x 12.8V or 1 x 25.6V	0.978	6 25/32"	10 19/64"	5 5/8"
TRA 750	TRA750/120V/12VAC OR 24VAC	750	120V	12V OR 24V	0.8 / 6.6 Amps	3 x 12.8V or 2 x 25.6V	0.98	4 19/32"	9 13/32"	4 3/32"
	TRA750/277V/12VAC OR 24VAC	750	277V	12V OR 24V	0.3 / 2.9 Amps	3 x 12.8V or 2 x 25.6V	0.98	4 19/32"	9 13/32"	4 3/32"
	TRA750/120V/12VDC OR 24VDC	750	120V	12V OR 24V	0.8 / 6.6 Amps	3 x 12.8V or 2 x 25.6V	0.98	4 19/32"	9 13/32"	4 3/32"
	TRA750/277V/12VDC OR 24VDC	750	277V	12V OR 24V	0.3 / 2.9 Amps	3 x 12.8V or 2 x 25.6V	0.98	4 19/32"	9 13/32"	4 3/32"
TRA 1000	TRA1000/120V/12VAC OR 24VAC	1000	120V	12V OR 24V	0.7 / 8.8 Amps	4 x 12.8V or 2 x 25.6V	0.98	6 25/32"	10 19/64"	5 5/8"
	TRA1000/277V/12VAC OR 24VAC	1000	277V	12V OR 24V	0.8 / 3.6 Amps	4 x 12.8V or 2 x 25.6V	0.98	6 25/32"	10 19/64"	5 5/8"
	TRA1000/120V/12VDC OR 24VDC	1000	120V	12V OR 24V	0.7 / 8.8 Amps	4 x 12.8V or 2 x 25.6V	0.98	6 25/32"	10 19/64"	5 5/8"
	TRA1000/277V/12VDC OR 24VDC	1000	277V	12V OR 24V	0.8 / 3.6 Amps	4 x 12.8V or 2 x 25.6V	0.98	6 25/32"	10 19/64"	5 5/8"
TRA 1200	TRA1200/120V/12VAC OR 24VAC	1200	120V	12V OR 24V	0.7 / 10.6 Amps	4 x 12.8V or 2 x 25.6V	0.98	6 25/32"	10 19/64"	5 5/8"
	TRA1200/277V/12VAC OR 24VAC	1200	277V	12V OR 24V	0.8 / 4.4 Amps	4 x 12.8V or 2 x 25.6V	0.98	6 25/32"	10 19/64"	5 5/8"
	TRA1200/120V/12VDC OR 24VDC	1200	120V	12V OR 24V	0.7 / 10.6 Amps	4 x 12.8V or 2 x 25.6V	0.98	6 25/32"	10 19/64"	5 5/8"
	TRA1200/277V/12VDC OR 24VDC	1200	277V	12V OR 24V	0.8 / 4.4 Amps	4 x 12.8V or 2 x 25.6V	0.98	6 25/32"	10 19/64"	5 5/8"

CALIFORNIA ACCENT LIGHTING, INC. 2034 E. Lincoln Ave. #431 Anaheim, CA. 92806

P. (714)535-7900 | F. (714)535-7902 | (800) 921-CALI (2254) | info@calilighting.com | www.calilighting.com

Copyright 2010 © CALI. All rights reserved. CALI reserves the right to make changes or withdraw specifications without prior notice.